



Product Name: Infrared Ceiling Fan Remote Control Kit

Product Model: AS-CF126N

ABR 爱普瑞

Make your life easy, make your home cozy

Features:


This unit includes a U-shaped receiver and a transmitter (remote control). Transmitter and receiver use infrared technology to communicate. The receiver fits well in the fan's canopy, installs horizontally above the ball attachment. It is designed for fans that vary their speeds by changing the capacitance in the circuit. It will work on almost all fans with lights in the market.

- Fan Speed: High/Medium/Low;
- Capacitance for fan speed: 4 μ F for Medium speed, 2 μ F for Low speed;
- Light function: On/Off
- Receiver with two infrared sensors installed at 180 degree opposite side out of the canopy, it can achieve 360 degree sensing range and no blind angle.
- Battery for remote control: One 6F22 9 Volts battery(not included)

Specifications:

Voltage	220~240V(50Hz/60Hz)	Operating temperature	0℃~55℃
Light load	600W(maximum)	Relative humidity	Non-condensing 20-90%
Motor load	150W(maximum)	Working distance	IR, \geq 5m (360°)
Receiver dimension	Radius (60mm)	Receiver weight	101g
Transmitter dimension	138*49*23mm	Transmitter weight	55g

 **Wiring Diagram:**



How to Order:

Please contact: Shenzhen Asia Bright Co., Ltd.
Floor 2nd~3rd, Building E, North Area No.2 of Shangxue
Science Park, Bantian, Shenzhen, China
Tel: +86-755-89602172/89748211
Email: sales@a-brt.com